

Paradox Evo 192 Dialler (done)

Programming sections for the Evo dialler

Basic Dialler Setup

Section 3036

- Option 3 must be **ON** to enable the dialler

Section 3061-3068 (Account Codes)

- 3061: Partition 1 account code
- 3062: Partition 2 account code

Section 3070 (Format)

- Enter **4 x 5** for Contact ID

Section 3071 (Telephone Number)

- Enter 5555555
-

Event Reporting Configuration

Sections 3127 to 3829

- Check partition options for event call directions
- These sections tell the panel what events need to be reported

Section 4031

- Enable all reporting codes for Contact ID
-

Important Programming Tips

After all programming:

1. **REBOOT the panel** - Critical step!
2. Disable the dialler module
3. Re-enable the dialler module, This clears the module for correct dialling.

Account Code Rules:

- **NEVER** use account codes starting with "0" (e.g., 0001)
 - Use 1001 instead
 - Can use hex A: 1AA1 (press "stay" button for hex A)
-

Troubleshooting

- If panel won't communicate after programming, always reboot
 - Disable/re-enable dialer module if issues persist
-

Revision #2

Created 30 July 2026 09:30:03 by Jonathan Cox

Updated 15 October 2026 07:33:51 by Jonathan Cox